

Busch Rotary Dimmer Flush Mounted Inserts Turn/push button



Busch Rotary Dimmer Flush Mounted Inserts Turn/push button 230V 2...360 V-A | 6523 UR-104-500

Article number:	2CKA006512A0354
Status product:	126 - CURRENT
Changed last:	28-05-2025
Brand:	ABB Busch-Jaeger
Type:	6523 UR-104-500
ETIM Group:	EG000013 - Domestic switching devices
ETIM Classes:	EC000025 - Dimmer
Synonym:	Adapter plug, Dimmer, Plug adapter



Feature

Assembly arrangement:	Basic element	Colour:	Black
Method of operation:	Turn/push button	Transparent:	No
App control via Bluetooth:	No	Suitable for degree of protection (IP):	IP20
Dimming phase cut-on:	Yes	Impact strength:	IK00
Dimming phase cut-off:	Yes	Nominal voltage:	230 ~ 230 V
Serial dimmer:	No	Frequency:	50 ~ 60 Hz
Type of load:	Universal and LED Retrofit	Control voltage:	220 ~ 240 V
Substation input:	No	Nominal power resistive load:	10 ~ 360 W
Light value memory:	Yes	Nominal power inductive load:	0 ~ 0 VA
Applicable with button:	No	Nominal power capacitive load:	0 ~ 0 VA
Applicable with movement sensor:	No	Max. switching power LED:	360 W
Applicable with presence indicator:	No	Connection type:	Screwed terminal
Applicable with time switch/timer:	No	Core cross section:	1 ~ 2.5 mm ²
Applicable with transmission button:	No	Device width:	71 mm
Applicable with infrared button:	No	Device height:	71 mm
Mounting method:	Flush-mounted	Device depth:	42 mm
Type of fastening:	Mounting with screw	Min. depth of built-in installation box:	20 mm
Material:	Plastic	Compatible with Apple HomeKit:	No
Material quality:	Thermoplastic	Compatible with Google Assistant:	No
Halogen free:	No	Compatible with Amazon Alexa:	No
Surface protection:	Untreated	IFTTT support available:	No
Surface finishing:	Matt		

Packaging data

Weight	0 gr
Customs code	85365080

